

PCX-PROX/INT TAG READER



Arming & access

Allowing authorised arming, disarming,
entry & exit

Whether users want an internal entry and exit controller or an internal arming and disarming solution, you can offer both with the PCX-PROX/INT internal tag reader.

www.pyronix.com

PCX-PROX/INT TAG READER



40mm



97mm

Partcode	FPCX-PROX/INT
Key Features	
Surface mounted	✓
Integrated prox reader	✓
Internal-use prox reader	✓
On-board inputs	2
On-board outputs	1
Electrical Specifications	
Power supply	12VDC (9-15v DC)
Current consumption	30mA
Inputs	2EOL
Outputs	150mA
Other Details	
Operating storage temperature	-10°C/+40°C -20°C/+60°C
Weight	130g
Dimensions	97 x 40 x 23mm
Warranty	2 years
Certifications	
Electrical conformity	CE
EN50131	Grade 3
Environmental class	II
	CA12.01420

Easy to use with proximity tag

The user can simply present a tag to the PCX-PROX/INT to arm/disarm the system or for access control.

Stylishly surface mounted

Sits perfectly against the wall to deliver a professional and pleasing finish.

Expand the system with programmable outputs & inputs

Through the PCX-PROX/INT an extra output and input can be added to the security system to add a contact, shock or any other device that the installation requires. It can be flexibly set up to have either two inputs or two outputs or one input and one output.

Meet the required security standard with Grading options

The PCX-PROX/INT is Grade 3 for the superior security the installation needs.

Know the status with backlit symbols

Whatever the status of the system, the PCX-PROX/INT will provide local indication with symbols for alert, alarm, tamper, fault and disarm.