

# PCX-RIX8I 8 INPUT EXPANDER



## Truly wired expansion

### Ultimate wired flexibility for any PCX control panel

Add any wired Pyronix peripheral to any PCX control panel to meet any installation needs! Select from the entire wired Pyronix range to easily cover extensions, outbuildings and much more.

Complies with EN50131-1

[www.pyronix.com](http://www.pyronix.com)

# PCX-RIX8I



## Deliver the inputs the installation needs with the ability to add 8 wired inertia inputs

This provides the ultimate flexibility for any PCX control panel to seamlessly expand the system. The PCX-RIX8i can utilise DEOL, SEOL, NC and inertia inputs or all eight inputs can be used as roller shutters.

## Beat the burglar with front & rear tamper protection

This ensures that maximum security is maintained against accidental or malicious tampering of the system, providing added peace of mind that the system is secure.

## Meet the required security standard with Grading options

The PCX-RIX8i is Grade 2 for the superior security the installation needs.

Partcode	PCX-RIX8I-P/BOX
<b>Type of Module</b>	
Wired input expander module	✓
Two-way wireless expander module	✗
Output expander module	✗
<b>Key Features</b>	
Wired inputs (NC/DEOL/3-EOL)	8†
Inertia and roller shutter sensors support	8
Output support	✗
Housing with tamper protection	Plastic
Integrated power supply	✗
Power input	9 - 15 DC
<b>Other Details</b>	
Operating   storage temperature	-10°C to +50°C   -20°C to +60°C
Weight	500g
Dimensions	173 x 125 x 32mm
Warranty	2 years
<b>Certifications</b>	
Electrical conformity	CE
EN50131	Grade 2
Environmental class	II
	CA12.01433

†Not compatible with 3-EOL inputs